

D132A Smoke Detector Reversing Relay Module

www.boschsecurity.com



BOSCH
Invented for life



- ▶ Allows compatible control panels to sound all smoke detectors within a loop during an alarm
- ▶ Mounts easily on any of the three-hole module mounting locations in a compatible control panel enclosure

The D132A Smoke Detector Reversing Relay Module allows compatible control panels to sound all smoke detectors connected to point 1 or zone 1 when a single detector on the loop goes into alarm.

Functions

Reverse Trigger

The reverse trigger requires a low input (short to ground) to activate. When activated, it reverses polarity on the detector loop.

Sounding Detectors in a Loop

When an alarm occurs within a loop connected to point 1 or zone 1, all detectors on that loop go into alarm. To restore the devices, the sensors must be reset.

Trouble Point

During normal operation the trouble point relay is normally closed (NC). During a trouble condition, the relay switches to normally open (NO).

Certifications and approvals

Region	Certification
USA	UL UTOU: Control Units and Accessories - Household System Type (UL985)
	CSFM see our website

Installation/configuration notes

Compatibility

Category	Manufacturer	Model Number*
Control Panels	Bosch	B-series panels ¹
		G-series panels ²
		D6412 and D4412 panels
Detectors	Bosch	D263THS Two-wire PIR smoke detector with 135°F (57°C) heat sensor and sounder
		D273THCS Four-wire PIR smoke detector with 135°F (57°C) heat sensor, auxiliary relay, and sounder

Category	Manufacturer	Model Number*
		D273THES Four-wire PIR smoke detector with 135°F (57°C) heat sensor, sounder, and EOL relay
		D273THS Four-wire PIR smoke detector with 135°F (57°C) heat sensor and sounder

¹ B-series = B5512, B4512 and B3512 panels

² G-series = D9412GV4, D7412GV4, D7212GV4, D9412GV3, D7412GV3, D7212GV3, D9412GV2, D7412GV2, D7212GV2

*For legacy products compatible with the D132A, see the *D132A Installation Instructions*.

Mounting Considerations

The module has a 3-hole pattern for easily mounting inside the control panel's enclosure. Mounting screws are provided.

Wiring Considerations

The module's terminal block accepts wire gauges from 22 AWG to 16 AWG (ISO 0.34 mm² to 1.5 mm²). The maximum detector circuit length is dependent on the wire gauge and the number of detectors on the loop.

Parts included

Quantity	Component
1	D132A module
1	Hardware pack containing 3 mounting screws
1	Installation Guide

Technical specifications

Electrical

Current (Alarm):	70 mA maximum
Current (Idle):	10 mA maximum
Voltage (Operating):	10.2 VDC to 13.9 VDC

Environmental

Environment	Indoor, dry
Operating Temperature:	+32°F to +120°F (0°C to +49°C)
Relative Humidity:	5% to 85% at +86°F (+30°C) non-condensing

Mechanical

Dimensions:	3 in. x 3 in. (7.6 cm x 7. cm)
-------------	--------------------------------

Ordering information

D132A Smoke Detector Reversing Relay Module

This module allows compatible control panels (G Series, B series, D6412 and D4412) to sound all smoke detectors connected to point 1 or zone 1 when

a single smoke detector on the loop goes into alarm. To restore the smoke detectors to normal, reset the smoke detectors.

Order number **D132A**

Represented by:

Americas:

Bosch Security Systems, Inc.
130 Perinton Parkway
Fairport, New York, 14450, USA
Phone: +1 800 289 0096
Fax: +1 585 223 9180
security.sales@us.bosch.com
www.boschsecurity.us

Europe, Middle East, Africa:

Bosch Security Systems B.V.
P.O. Box 80002
5617 BA Eindhoven, The Netherlands
Phone: + 31 40 2577 284
Fax: +31 40 2577 330
emea.securitysystems@bosch.com
www.boschsecurity.com

Asia-Pacific:

Robert Bosch (SEA) Pte Ltd, Security
Systems
11 Bishan Street 21
Singapore 573943
Phone: +65 6571 2808
Fax: +65 6571 2699
apr.securitysystems@bosch.com
www.boschsecurity.asia

China:

Bosch (Shanghai) Security Systems Ltd.
201 Building, No. 333 Fuquan Road
North IBP
Changning District, Shanghai
200335 China
Phone +86 21 22181111
Fax: +86 21 22182398
www.boschsecurity.com.cn

America Latina:

Robert Bosch Ltda Security Systems Division
Via Anhanguera, Km 98
CEP 13065-900
Campinas, Sao Paulo, Brazil
Phone: +55 19 2103 2860
Fax: +55 19 2103 2862
latam.boschsecurity@bosch.com
www.boschsecurity.com