

# EN4204R Wireless LED Receiver

www.boschsecurity.com



**BOSCH**  
Invented for life



- ▶ Monitors up to four transmitters or repeaters
- ▶ Cost-effective solution for small systems
- ▶ Flexible alarm and fault output
- ▶ Wireless registration
- ▶ Compatible with a variety of transmitters and control panels

The EN4204R LED Receiver integrates up to four 900 MHz wireless transmitters into any application. The Inovonics EchoStream platform uses diversity reception and advanced signal processing to reduce dead spots in transmission areas. The LED clearly shows the current status for each transmitter. The receiver provides versatile options for adding high performance wireless to an installation.

## System overview

### Powered by Inovonics

The Inovonics EchoStream platform, powered by Inovonics wireless mesh network technology, ensures superior range, reliability, and scalability for commercial applications. Using a wide range of transmitters and repeaters, this proven technology provides flexibility and performance to meet the most stringent requirements. This exclusive protocol is available only on Inovonics EchoStream products.

### Wireless 900 MHz Band

The Inovonics EchoStream platform sends redundant information on several multi-frequency channels within the FCC Part 15 900 MHz band, providing superior range and reliability. In comparison, systems that use a single frequency technology can only send information on one narrow band channel. Any interference within

the band can cause missed signals. With wireless registration, it is easy to add this technology to any application.

## Functions

### Flexible Outputs

Transmitters and repeater faults and alarms map to any of the receiver models.

### Wireless Registration

There is no external programmer required. The transmitter is enrolled using a wireless programming routine built into the receiver. Wireless registration reduces installation time.

### Secure Wireless Implementation

Jam detection monitors all channels for the presence of interference for more than 20 sec. A reset terminal is inside the receiver, allowing the receiver to accept external reset signals. The receiver includes case tamper and internal antennas for added security.

### Status Indication

LEDs show the current condition of each transmitter, including activation, tamper, low battery, and inactivity.

### Supervision and Expansion

Transmitter supervisory check-in and a transmitter specific supervisory window, defined in the receiver, support sites with both removable pendants and fixed-position transmitters. The technology also supervises repeaters.

Enroll, supervise, and map up to four wireless transmitters and repeaters using the appropriate outputs. Configure transmitters and repeaters individually to best suit the application. Each includes a fifth output used for fault reporting.

### Certifications and approvals

Inovonics Wireless Corporation holds the following approvals:

FCC Conforms to FCC Part 15 regulations

### Installation/configuration notes

#### Compatibility Information

The EN4204R LED Receiver is compatible with the following products:

#### Repeater

EN5040-T	High-power Repeater
----------	---------------------

#### Transmitters

EN1210	Universal Transmitter (Single-input)
EN1210EOL	Universal Transmitter with EOL Resistor
EN1210SK	Survey Transmitter
EN1210W	Door-Window Transmitter with Reed Switch
EN1215EOL	Universal Transmitter with Wall Tamper and EOL Resistor
EN1215WEOL	Door-Window Transmitter with Wall Tamper, Reed Switch, and EOL Resistor
EN1223D	Water-resistant Pendant Transmitter (Double-button)
EN1223S	Water-resistant Pendant Transmitter (Single-button)
EN1223SK	Survey Pendant Transmitter
EN1233D	Necklace Pendant Transmitter (Double-button)
EN1233S	Necklace Pendant Transmitter (Single-button)
EN1235D	Beltclip Pendant Transmitter (Double-button)
EN1235S	Beltclip Pendant Transmitter (Single-button)
EN1235DF	Fixed-location Transmitter (Double-button)
EN1235SF	Fixed-location Transmitter (Double-button)
EN1242	Smoke Detector-Transmitter
EN1247	Glass-break Sensor Transmitter
EN1249	Billtrap Transmitter

EN1260	PIR Motion Sensor-Transmitter (Commercial and High-end Domestic Applications)
EN1261HT	PIR Motion Sensor-Transmitter (High-traffic Areas)
EN1262	PIR Motion Sensor-Transmitter (Residential and Low-traffic Commercial Applications)
EN1265	PIR Motion Sensor-Transmitter (Ceiling-mount Applications)

### Parts included

Quant.	Component
1	EN4204R Receiver
1	Hardware pack
1	Literature – Installation and Operation Manual

### Technical specifications

#### Electrical

Power Requirements:	10 VDC to 14 VDC
---------------------	------------------

#### Outputs

Rating:	1 A, 28 VDC, or 0.5 A, 30 VAC (resistive)
Types:	<ul style="list-style-type: none"> <li>Four Form C relays for connecting to any control panel or for stand-alone wireless applications (NO or NC)</li> <li>One NO Receiver case tamper contact closure</li> <li>One NC Receiver jam input indication</li> </ul>

#### Environmental

Relative Humidity:	Up to 90%, non-condensing
Temperature (operating):	0°C to +60°C (+32°F to +140°F)

#### Mechanical

Material:	ABS
Closure:	Latching with optional screws for high security installations
Dimensions:	16.5 cm x 8.9 cm x 2.5 cm (6.5 in. x 3.5 in. x 1 in.)
Weight:	204 g (7.2 oz)

#### Reception Characteristics

Frequency Compatibility:	902 MHz to 928 MHz
Transmitters:	Supports up to four

#### Trademarks

Trademark names are used throughout this document. In most cases, these designations are claimed as trademarks or registered trademarks in one or more countries by their respective owners. Rather than

placing a trademark symbol in every occurrence of a trademark name, Bosch Security Systems, Inc. uses the names only in an editorial fashion and to the benefit of the trademark owner with no intention of infringing the trademark.

Inovonics is a trademark of Inovonics Wireless Corporation.

## Ordering information

### EN4204R Wireless LED Receiver

Monitors up to four wireless transmitters or repeaters.  
Order number **EN4204R**

#### Represented by:

##### Americas:

Bosch Security Systems, Inc.  
130 Perinton Parkway  
Fairport, New York, 14450, USA  
Phone: +1 800 289 0096  
Fax: +1 585 223 9180  
security.sales@us.bosch.com  
www.boschsecurity.us

##### Europe, Middle East, Africa:

Bosch Security Systems B.V.  
P.O. Box 80002  
5617 BA Eindhoven, The Netherlands  
Phone: + 31 40 2577 284  
Fax: +31 40 2577 330  
emea.securitysystems@bosch.com  
www.boschsecurity.com

##### Asia-Pacific:

Robert Bosch (SEA) Pte Ltd, Security Systems  
11 Bishan Street 21  
Singapore 573943  
Phone: +65 6571 2808  
Fax: +65 6571 2699  
apr.securitysystems@bosch.com  
www.boschsecurity.asia

##### China:

Bosch (Shanghai) Security Systems Ltd.  
201 Building, No. 333 Fuquan Road  
North IBP  
Changning District, Shanghai  
200335 China  
Phone +86 21 22181111  
Fax: +86 21 22182398  
www.boschsecurity.com.cn

##### America Latina:

Robert Bosch Ltda Security Systems Division  
Via Anhanguera, Km 98  
CEP 13065-900  
Campinas, Sao Paulo, Brazil  
Phone: +55 19 2103 2860  
Fax: +55 19 2103 2862  
latam.boschsecurity@bosch.com  
www.boschsecurity.com