

FMR-7036 Fire Annunciator Keypad

www.boschsecurity.com



BOSCH
Invented for life



- ▶ Compatible with FPD-7024 Fire Alarm Control Panel
- ▶ Two-line, 16-character LCD display
- ▶ On-board LEDs indicate Silenced, Trouble, Alarm, and Supervisory
- ▶ Silence and Reset buttons
- ▶ Built-in keyswitch

The FMR-7036 is a four-wire LCD annunciator keypad used with the FPD-7024 Fire Alarm Control Panel (FACP) to establish the location of a fire alarm. The two-line, 16-character display is capable of showing all messages normally displayed on the control panel. All alarm and status messages are included. Four on-board LEDs provide easy reading of the annunciator's status from a distance. There are Silence and Reset buttons for controlling annunciator and control panel operation. A built-in keyswitch offers extra security by locking the annunciator to prevent unwanted sounder silencing or control panel resetting.

Certifications and approvals

Region	Certification	
USA	UL	UQJZ: Control Units, System (ANSI/UL 864)
	FM	FMR-7036
	CSFM	see our website
	FDNY-CoA	#6173

Installation/configuration notes

Compatible Products

Category	Product ID	Product Description
Control Panels	FPD-7024	Four-zone FACP

Mounting

The FMR-7036 can be surface mounted on a standard three-gang box, or with the mounting backplate provided.

Wiring Guidelines

For the FPD-7024 FACP, the maximum allowed DC current draw from the option bus is 500 mA for keypads. The maximum length of wire (all branches added together) that can be connected to the option bus terminals is 4000 ft (1220 m). The maximum length between any one device and the control panel terminals depends on the current draw on the branch that the device is on. The current draw on a particular branch can be found by adding together the individual current draws of each device connected to the branch.

**Notice**

Refer to the *FPD-7024 Installation Guide* (P/N: F01U008458) for complete wire length calculations.

Number of Keypads

Up to four keypads can be used per system. Up to three keypads can be used on any single 1000 ft (305 m) run of 18 AWG (1.2 mm) wire.

Parts included

Quant.	Component
1	LCD annunciator keypad
1	Literature pack

Technical specifications**Environmental Considerations**

Environment:	Indoor, dry
Relative Humidity:	Up to 95%, non-condensing
Temperature (operating):	+32°F to 120°F (0°C to +49°C)

Mechanical Properties

Base Dimensions (HxW):	4.6 in. x 8.2 in. (11.7 cm x 20.8 cm)
Cover Dimensions (HxW):	4.3 in. x 8.1 in. (10.9 cm x 20.6 cm)

Power Requirements

Current (Alarm):	100 mA
Current (Standby):	80 mA nominal
Voltage (Operating):	12 VDC nominal

Ordering information**FMR-7036 Fire Annunciator Keypad**

Four-wire LCD annunciator keypad used with the FPD-7024 Fire Alarm Control Panel to establish the location of a fire alarm

Order number **FMR-7036**

Accessories**KEY-ANN Replacement Key**

This is a replacement key for the lock used on most Bosch Security Systems, Inc. annunciators and key switches.

Order number **KEY-ANN**

Represented by:**Americas:**

Bosch Security Systems, Inc.
130 Perinton Parkway
Fairport, New York, 14450, USA
Phone: +1 800 289 0096
Fax: +1 585 223 9180
security.sales@us.bosch.com
www.boschsecurity.us

Europe, Middle East, Africa:

Bosch Security Systems B.V.
P.O. Box 80002
5617 BA Eindhoven, The Netherlands
Phone: + 31 40 2577 284
Fax: +31 40 2577 330
emea.securitysystems@bosch.com
www.boschsecurity.com

Asia-Pacific:

Robert Bosch (SEA) Pte Ltd, Security Systems
11 Bishan Street 21
Singapore 573943
Phone: +65 6571 2808
Fax: +65 6571 2699
apr.securitysystems@bosch.com
www.boschsecurity.asia

China:

Bosch (Shanghai) Security Systems Ltd.
201 Building, No. 333 Fuquan Road
North IBP
Changning District, Shanghai
200335 China
Phone +86 21 22181111
Fax: +86 21 22182398
www.boschsecurity.com.cn

America Latina:

Robert Bosch Ltda Security Systems Division
Via Anhanguera, Km 98
CEP 13065-900
Campinas, Sao Paulo, Brazil
Phone: +55 19 2103 2860
Fax: +55 19 2103 2862
latam.boschsecurity@bosch.com
www.boschsecurity.com