

## HAL-EMG-48-60W-ITG-LED

### 60 Watt Hazardous Location Integrated LED Light Fixture

Do not attempt installation until you are familiar with all warnings, precautions, and procedures outlined within this instruction sheet.

#### INSTALLATION PRECAUTIONS

- Do not install fixture in any classified location where the marked operating temperature exceeds the ignition temperature of the hazardous atmospheres. Consult fixture nameplate for the suitability ambient temperature shown on the nameplate. Refer to fixture nameplate for minimum supply wire temperature rating.
- Verify that the supply voltage agrees with fixture rating as indicated on nameplate. All local and national electrical/building codes must be followed when installing this lighting fixture. For code interpretation, consult your local authority. Product must be used only with lens intact and all cap threads fully engaged. Do not use if lens is cracked or damaged.

**Caution:** Only use lamp size, type and /or wattage as shown on fixture nameplate.

#### INSTALLATION

*We strongly recommend that only a licensed electrician install this product.*

**WARNING:** *Make sure that the power is disconnected before installing. This fixture is extremely heavy and must be mounted to a surface that can structurally support the load. An optional drop mounting kit that will allow for end to end row mounting is available, please consult factory.*

**WARNING:** *Do not let fixture hang on one bracket at any time. Failing to comply can result in breakage of and end casting or mounting bracket allowing the fixture to fall which can cause serious injury or death.*

- The mounting brackets are shipped installed on the fixture.
- Install the fixture via these brackets to wall or ceiling.

Check fixture nameplate for proper voltage!

**Voltage: 120/277V AC 60Hz**

#### WIRING

- Install approved cable connector or conduit fitting into NPT hub on field wiring compartment.
- Install a three conductor cable into the connector, allowing 3 inches of wire inside compartment for connection. Open access plate for access to wire terminal block.
- Use terminal blocks inside fixture for wiring, splice wires as per color codes: black to black (line) white to white (common) and green to green (ground).
- Make sure there are no wires protruding that maybe pinched causing a possible short circuit.
- See emergency backup ballast operation on next page.

**WARNING:** *Fixture must be grounded as required per paragraph 410-21 and article 250 of the National Electric Code and/or rule 30-500. Failure to properly ground this fixture will create and electrical shock, which can cause serious injury or death.*

## EMERGENCY BACKUP BALLAST OPERATION

During normal operation, AC power is supplied to the ballast through the backup micro inverter and the inverter charges the battery. Connecting the inverter wires (red and white) enables the emergency circuit and supplies power to the control/monitor circuit. The backup micro inverter detects AC input voltage and automatically sets the output voltage during emergency operation. When AC power fails, the backup micro inverter automatically switches to emergency mode, keeping the load illuminated for a minimum of 90 minutes. When AC power is restored, the backup micro inverter returns to charge mode to recharge the battery. The backup micro inverter consists of a low battery voltage disconnect which is reset when AC power is restored. The unit can also detect an abnormal load condition (open or shorted load) during emergency mode operation and will protect the inverter from damage.

## MAINTENANCE

Although no routine maintenance is required to keep the backup micro inverter functional, it should be checked periodically to ensure that it is working. The following schedule is recommended:

1. Visually inspect the charging indicator light monthly. It should be illuminated.
2. Test the emergency operation of the fixture at 30-day intervals for a minimum of 30 seconds. The lamp should operate at full illumination.
3. Conduct a 90-minute discharge test once a year. The lamp should operate at full illumination for at least 90 minutes.

## REPLACEMENT PARTS

The HAL-EMG-48-60W-ITG-LED is designed to provide years of reliable lighting performance. Should the need for replacement parts arise, please contact Larson Electronics at the contact information below.

Should further information not covered by these instructions be required, please contact Larson Electronics at 1-800-369-6671 or [sales@larsonelectronics.com](mailto:sales@larsonelectronics.com) for further assistance.

Please visit [LarsonElectronics.com](http://LarsonElectronics.com) for Warranty and Return information.