

# FA116 Executive Programmer

www.boschsecurity.com



**BOSCH**  
Invented for life



- ▶ Reliable communication through 900 MHz spread spectrum technology with frequency hopping
- ▶ False alarm reduction through 56 bit communication protocol and advanced signal processing
- ▶ Programs all multi-channel receivers
- ▶ Sets receiver and transmitter parameters
- ▶ Permits transmitter zoning

Use the FA116 Executive Programmer to alter receiver and transmitter parameters to fit specific applications. You can also use it to monitor the signal margin of points, test output functions, clear faults, and to add, modify, delete and program transmitters. Use the menu-driven option screens to accept, change, or reject current settings for the receiver, receiver output, and transmitters.

## Installation/configuration notes

### Compatibility Information

Control Panels	D9412GV2, D7412GV2, and D7212GV2 D9412G, D7412G, v6.30 or higher D7212G, v6.41 or higher
Wireless Interface Modules	D8125INV
Receivers	FA400, FA404R, and FA416R

## Technical specifications

### Mechanical

Color:	Black
Weight:	309 g (10.9 oz)
Display Dimensions:	1.9 cm x 6.1 cm (0.625 in. x 2.4 in.)
Overall Dimensions:	17.8 cm x 9.9 cm x 4.4 cm (7.0 in. x 3.9 in. x 1.75 in.)

### Environmental

Relative Humidity:	Up to 95% non-condensing
Temperature (operating):	0°C to +60°C (+32°F to +140°F)

## Ordering information

### FA116 Executive Programmer

Alters receiver and transmitter parameters to fit specific applications  
Order number **FA116**

---

**Accessories**

**Programming Cable**

Connects an Inovonics transmitter to the FA116 Executive Programmer  
Order number **ACC620**

---

**Transfer Programmer**

Allows reprogramming an Inovonics transmitter without moving it  
Order number **ACC630**

---

**Represented by:**

**Americas:**

Bosch Security Systems, Inc.  
130 Perinton Parkway  
Fairport, New York, 14450, USA  
Phone: +1 800 289 0096  
Fax: +1 585 223 9180  
security.sales@us.bosch.com  
www.boschsecurity.us

**Europe, Middle East, Africa:**

Bosch Security Systems B.V.  
P.O. Box 80002  
5617 BA Eindhoven, The Netherlands  
Phone: + 31 40 2577 284  
Fax: +31 40 2577 330  
emea.securitysystems@bosch.com  
www.boschsecurity.com

**Asia-Pacific:**

Robert Bosch (SEA) Pte Ltd, Security Systems  
11 Bishan Street 21  
Singapore 573943  
Phone: +65 6571 2808  
Fax: +65 6571 2699  
apr.securitysystems@bosch.com  
www.boschsecurity.asia

**China:**

Bosch (Shanghai) Security Systems Ltd.  
201 Building, No. 333 Fuquan Road  
North IBP  
Changning District, Shanghai  
200335 China  
Phone +86 21 22181111  
Fax: +86 21 22182398  
www.boschsecurity.com.cn

**America Latina:**

Robert Bosch Ltda Security Systems Division  
Via Anhanguera, Km 98  
CEP 13065-900  
Campinas, Sao Paulo, Brazil  
Phone: +55 19 2103 2860  
Fax: +55 19 2103 2862  
latam.boschsecurity@bosch.com  
www.boschsecurity.com