

D1255RB Fire Keypad

www.boschsecurity.com



BOSCH
Invented for life



- ▶ Compatible with several combined intrusion/fire control panels by Bosch.
- ▶ Built-in multi-tone sounder
- ▶ Easy to read vacuum fluorescent display (VFD) shows complete system status in English
- ▶ Easy system control with menu keys
- ▶ User controlled brightness and volume

The D1255RB Fire Keypad is a full-function system controller and annunciator. This SDI bus device works with several combined intrusion/fire control panels by Bosch. The illuminated keypad has a 16-character vacuum fluorescent display (VFD) with each character a 14-segment unit and a sounder that emits distinct condition tones.

Functions

Display

The display uses words, numbers, and symbols to show the status of the fire system. When several events occur, each event is shown in order of priority followed by the time of occurrence. In conjunction with the 16-character VFD, four LEDs provide the following system status indications:

- Fire
- Silenced
- Supervisory
- Trouble

Keys

The keypad has ten numeric keys and five function keys. Use the [COMMAND] key with the numeric keys to perform a function. Use the [ENT] key or [YES] key to enter your passcode. When pressed, each key emits light and a muted beep.

Audible Tones

The sounder emits distinct warning tones. You can adjust the volume or use a passcode to silence the tone. The tones include:

- Fire signal: pulsed high-pitched bell tone during fire alarm
- Invalid key buzz: buzz tone when invalid key is pressed
- Keypad encoding tone: muted beep tone as each key is pressed
- Trouble buzz: two-tone warble during a trouble event

Certifications and approvals

Region	Certification	
USA	UL	UOXX: Control Unit Accessories, System (ANSI/UL 864)
	FM	
	CSFM	see our website

Region	Certification
	FDNY-CoA 6174
	FDNY-CoA 6059 [D9412GV3 & D7412GV3]
	FDNY-CoA 6196

Installation/configuration notes

Compatible Control Panels

- B9512G/B9512G-E
- B8512G/B8512G-E
- D9412GV4/D7412GV4/D7212GV4¹
- D9412GV3/D7412GV3/D7212GV3¹
- D9412GV2/D7412GV2/D7212GV2¹

¹The D7212GV4, D7212GV3, and D7212GV2 are not listed for commercial fire applications.

Mounting Considerations

The keypad is a low profile, surface-mounted unit molded in durable red plastic with three mounting holes in the base that allow secure, correct positioning during installation. Protect the surface-mounted keypad by mounting it to a D56 or D56R Conduit Back Box. For desktop applications, the keypad can be mounted to a D55 Desk Stand.



Notice

Do not install the keypad in direct sunlight. This damages the module components and makes the display less visible. Do not mount in wet or moist locations.

Wiring Considerations

The keypad connects to the control panel for data and power through a standard four-wire flying lead cable. For field wiring use 0.8 mm (22 AWG) or 1.2 mm (18 AWG) wires. Resistance cannot exceed 25 Ω. The field wiring connects to a four-wire harness supplied with the unit.



Notice

Use shielded cable where excessive electromagnetic interference is a problem.

Trademarks

All hardware and software product names used in this document are likely to be registered trademarks and must be treated accordingly.

Parts included

Quantity	Component
1	Keypad
1	Hardware pack
1	Literature pack

Technical specifications

Environmental Considerations

Relative humidity	5% to 93% at +32°C (+90°F)
Temperature (operating)	0°C to +49°C (+32°F to +120°F)

Mechanical Properties

Color:	Red and gray
Dimensions:	11.7 cm x 21 cm x 2 cm (4.6 in. x 8.2 in. x 0.8 in.)
Material:	CHI MEI POLYLAC PA757 ABS with UV Stabilizer. UL94-HB Fire Rated

Power Requirements

Current:	104 mA minimum, 225 mA maximum
Voltage:	12 VDC nominal supplied by the control panel

Ordering information

D1255RB Fire Keypad

Red and gray case.

Order number **D1255RB**

Accessories

D55 Keypad Desk Stand

Portable desk stand in smoke colored Plexiglas.

Order number **D55**

D56 Surface Mount Conduit Box

White surface mount box.

Order number **D56**

D56R Red Surface Mount Conduit Box

Red surface mount box.

Order number **D56R**

Represented by:

North America:

Bosch Security Systems, Inc.
130 Perinton Parkway
Fairport, New York, 14450, USA
Phone: +1 800 289 0096
Fax: +1 585 223 9180
security.sales@us.bosch.com
www.boschsecurity.us

Europe, Middle East, Africa:

Bosch Security Systems B.V.
P.O. Box 80002
5617 BA Eindhoven, The Netherlands
Phone: + 31 40 2577 284
Fax: +31 40 2577 330
emea.securitysystems@bosch.com
www.boschsecurity.com

Asia-Pacific:

Robert Bosch (SEA) Pte Ltd, Security
Systems
11 Bishan Street 21
Singapore 573943
Phone: +65 6571 2808
Fax: +65 6571 2699
apr.securitysystems@bosch.com
www.boschsecurity.asia

China:

Bosch (Shanghai) Security Systems Ltd.
203 Building, No. 333 Fuquan Road
North IBP
Changning District, Shanghai
200335 China
Phone +86 21 22181111
Fax: +86 21 22182398
www.boschsecurity.com.cn

Latin America and Caribbean:

Robert Bosch Ltda Security Systems Division
Via Anhanguera, Km 98
CEP 13065-900
Campinas, Sao Paulo, Brazil
Phone: +55 19 2103 2860
Fax: +55 19 2103 2862
latam.boschsecurity@bosch.com
www.boschsecurity.com