

# D1256RB Fire Keypad

www.boschsecurity.com



**BOSCH**  
Invented for life



- ▶ Compatible with Bosch GV3 control panels and GV2 control panels (firmware version 7.04 and higher)
- ▶ Provides system control with easy to use function keys
- ▶ Built-in multi-tone sounder
- ▶ Easy to read vacuum-fluorescent display (VFD) shows complete system status in English
- ▶ Programmable custom text for each point

The D1256RB Fire Keypad is a full-function system controller and annunciator. This SDI bus compatible device works with the Bosch Security Systems, Inc. GV3 control panels and GV2 control panels (firmware version 7.04 and higher). Four one-touch function keys provide user-friendly control over the system. The function keys allow the user to silence the audible alarm output, silence the trouble sounder, reset the annunciator display, and reset the system detectors. Four additional navigational keys allow access to other programmed system functions. The D1256RB can be mounted in secure areas.

## Functions

### Display

The display uses words, numbers, and symbols to show the status of the fire system. When several events occur, each event is shown in order of priority followed by the time of occurrence. In conjunction with the 16-character vacuum-fluorescent display (VFD), four LEDs provide the following system status indications:

- Fire
- Silenced
- Supervisory
- Trouble

## Certifications and approvals

Region	Certification	
USA	UL	UOXX: Control Unit Accessories, System (ANSI/UL 864)
	FM	
	CSFM	see our website
	FDNY-CoA	6174
	FDNY-CoA	6059 [D9412GV3 & D7412GV3]
	FDNY-CoA	6196

## Installation/configuration notes

### Compatible Control Panels

- B9512G/B9512G-E
- B8512G/B8512G-E
- D9412GV4/D7412GV4/D7212GV4<sup>1</sup>
- D9412GV3/D7412GV3/D7212GV3<sup>1</sup>
- D9412GV2/D7412GV2/D7212GV2<sup>1</sup>

<sup>1</sup>The D7212GV4, D7212GV3, and D7212GV2 are not listed for commercial fire applications.

### Mounting Considerations

The keypad is a low profile, surface-mounted unit molded in durable red plastic with three mounting holes in the base that allow secure, correct positioning during installation. Protect the surface-mounted keypad by mounting it to a D56 or D56R Conduit Back Box. For desktop applications, the keypad can be mounted to a D55 Desk Stand.



#### Notice

Do not install the keypad in direct sunlight. This damages the module components and makes the display less visible. Do not mount in wet or moist locations.

### Wiring Considerations

The keypad connects to the control panel for data and power through a standard four-wire flying lead cable. For field wiring use 0.8 mm (22 AWG) or 1.2 mm (18 AWG) wires. Resistance cannot exceed 25 Ω. The field wiring connects to a four-wire harness supplied with the unit.



#### Notice

Use shielded cable where excessive electromagnetic interference is a problem.

### Trademarks

All hardware and software product names used in this document are likely to be registered trademarks and must be treated accordingly.

### Parts included

Quant.	Component
1	Keypad
1	Hardware pack
1	Literature pack

### Technical specifications

#### Environmental Considerations

Relative humidity	5% to 93% at +32°C (+90°F)
Temperature (operating)	0°C to +49°C (+32°F to +120°F)

#### Mechanical Properties

Color:	Red
Dimensions:	11.7 cm x 21 cm x 2 cm (4.6 in. x 8.2 in. x 0.8 in.)
Material:	CHI MEI POLYLAC PA757 ABS with UV Stabilizer. UL94-HB Fire Rated

### Power Requirements

Current:	104 mA minimum, 225 mA maximum
Voltage:	12 VDC nominal supplied by the control panel

### Ordering information

#### D1256RB Fire Keypad

The D1256RB Fire Keypad provides our one-touch function keys for user-friendly control over the system  
Order number **D1256RB**

#### Accessories

##### D55 Keypad Desk Stand

Portable desk stand in smoke colored Plexiglas.  
Order number **D55**

##### D56 Surface Mount Conduit Box

White surface mount box.  
Order number **D56**

##### D56R Red Surface Mount Conduit Box

Red surface mount box.  
Order number **D56R**

**Represented by:**

**Europe, Middle East, Africa:**  
Bosch Security Systems B.V.  
P.O. Box 80002  
5600 JB Eindhoven, The Netherlands  
Phone: + 31 40 2577 284  
emea.securitysystems@bosch.com  
emea.boschsecurity.com

**North America:**  
Bosch Security Systems, Inc.  
130 Perinton Parkway  
Fairport, New York, 14450, USA  
Phone: +1 800 289 0096  
Fax: +1 585 223 9180  
onlinehelp@us.bosch.com  
www.boschsecurity.us

**Asia-Pacific:**  
Robert Bosch (SEA) Pte Ltd, Security Systems  
11 Bishan Street 21  
Singapore 573943  
Phone: +65 6571 2808  
Fax: +65 6571 2699  
apr.securitysystems@bosch.com  
www.boschsecurity.asia