



Larson Electronics LLC www.LarsonElectronics.com sales@larsonelectronics.com
9419 E US HWY 175, Kemp, TX 75143 - P: (800) 369-6671 - F: (903) 498-3364

Tube Repair Instructions for Larson Electronics EPL Series

- 1) Using appropriate safety precautions remove both Pyrex tubes. Chip out and remove all glass and cement (Chico) that remains in the fixture tube ends.
- 2) Thoroughly clean all cavities and ensure all surfaces are clean of glass and Chico (cement).
- 3) Lay the fixture down on the surface, face up with re-lamping end towards you. Insert gaskets and tubes. Place blind casting (no hub side) on the other end of the Pyrex tubing. If possible, apply tension or weight to blind casting end, pushing fixture together.
- 4) Mix cement per instructions on container and pour in between the glass and castings.
- 5) Allow cement to dry
- 6) Rotate lamp 180 degrees and repeat steps 1-5.