

## 20A Explosion Proof Ground Fault Circuit Interrupter w/ Red Indicator Light - GFCI - Malleable Iron Body

### EXP-GFCI-20A-PLR

Please see last page for supporting documentation for this product(certificates, CAD files & drawings, IES files, wiring diagrams, etc).



#### EXP-GFCI-20A-PLR Explosion Proof GFCI w/ Red Indicator Light

Listing: NRTL Listed for United States, Canada

Type: Explosion Proof Ground Fault Circuit Interrupter

Dimensions: -

Voltage: 125V AC

Amps: 20A

Trip Setting: 6mA

Indicator Light: Red

Body Materials: Malleable Iron

Hardware Materials: Stainless Steel

Finish: Baked Grey Epoxy

Configuration: Feed-Thru or Dead-End

Hubs: 1/2" or 3/4"

#### Ratings/Features

Class I, Divisions 1 & 2 Groups B, C and D

Class II, Divisions 1 & 2 Groups E, F and G

Class III

NEMA 3, 3R, 7 (Groups B,C,D) and 9 (Groups E,F,G)

#### Special Orders- Requirements

Contact us for special requirements

Toll Free: 1-800-369-6671

Intl: 1-214-616-6180

Fax: 1-903-498-3364

E-mail: [sales@larsonelectronics.com](mailto:sales@larsonelectronics.com)

**The Larson Electronics EXP-GFCI-20A-PLR Explosion Proof Ground Fault Circuit Interrupter (GFCI) with Red Indicator Light provides protection for electrically operated devices. This explosion proof GFCI is rated for Class I, Divisions 1 & 2 Groups B, C and D, Class II, Divisions 1 & 2 Groups E, F and G and Class III hazardous areas. The EXP-GFCI-20A-PLR is ideal for use in environments with corrosive atmospheres, wet locations and in areas that contain potentially explosive gases, dusts or other hazardous materials.**

The EXP-GFCI-20A-PLR is factory sealed and constructed from malleable iron. The smooth-operating test and reset buttons are made from stainless steel along with the button shafts and the cover bolts. A red indicator light turns on when the GFCI is tripped and must be reset. This explosion proof 20-amp GFCI is rated NEMA 3, 3R, 7 (Groups B,C,D) and 9 (Groups E,F,G) making it suitable for indoor and outdoor operation within hazardous areas. The EXP-GFCI-20A-PLR also features a baked grey epoxy clad finish for increased durability.

The EXP-GFCI-20A-PLR is rated for 20 amps and 125V AC and has a 5mA trip setting. This explosion proof ground fault circuit interrupter is available with both 1/2" and 3/4" hubs and in either a feed-thru or dead-end configuration.

At Larson Electronics, we do more than meet your lighting needs. We also provide replacement, retrofit, and upgrade parts as well as industrial grade power accessories. Our craftsmen can custom build any lighting system and/or



accessories to fit the unique demands of your operation. A commitment to honesty, quality, and dependability has made Larson Electronics a leader in the lighting and electronics business since 1973. Contact us today at 800-369-6671 or message [sales@larsonelectronics.com](mailto:sales@larsonelectronics.com) for more information about our custom options tailored to meet your specific industry needs.

---



---

## Frequently Asked Questions (FAQ)

**Options:**

**EXP-GFCI-20A-PLR-Hub Config-Configuration**

**Example: EXP-GFCI-20A-PLR-0.5IN-FT**

Hub Config	
1/2	-0.5IN
3/4	-0.75IN

Configuration	
FEED-THRU	-FT
DEAD-END	-DE

Links (Click on the below items to view):

- [HigResPic1](#)
- [ISO 9001 Certification](#)
- [Business Certificate](#)