

## 18W Red LED Bulb - 4' T8 Lamp - 2250 Lumens - Dual Power Ends - Replacement or Upgrade for Fluorescent

**LEDT8-18W-V1-C-RED-X2**

**Please see last page for supporting documentation for this product(certificates, CAD files & drawings, IES files, wiring diagrams, etc).**



### LEDT8-18W-V1-C-RED-X2 28 watt T-series Fluorescent Style LED Tube

NRTL Listed for United States & Canada

**Lamp Type:** LED T8-Style Tube (Dual Power Ends)

**Base:** G13 Bi-Pin

**Dimensions:** 47"-L x 1.03"-OD

**Weight:** 0.77 lbs (350 grams)

**Voltage:** 100-277 Volts AC, 50/60Hz or 11-25 Volts AC/DC

**Watts:** 18 watts

**Total Lumens:** 2,250

**Luminous Efficiency:** 125 lm/w

**Lamp Life Expectancy:** 50,000+ Hours

**Color:** Red

**Color Rendering Index:** 85+

**Beam angle:** 150°

**Lighting Configuration:** Flood Pattern

**Lens:** Clear, Frosted, Heavy Frosted

**Power Efficiency:** 90%

**Power Factor:** >0.95

**Ambient Temperature Rating:** -40°C to +65°C

**Materials:** Aluminum housing, polycarbonate lens

**Ingress Protection:** IP20

### Quick Summary

Listed for United States and Canada

NRTL Certified to UL-1993

NRTL Certified to UL-1993 CLS

NRTL Certified to CAN/CSA C22.2 No 1993

80% Lumen Retention @ 50,000+ Hours

125 lm/w efficiency

Internal Driver

Dual End Powered

Line Voltage On One End, Neutral on Other

LEL Listed

### Special Orders- Requirements

Contact us for special requirements

**Toll Free:** 1-800-369-6671

**Intl:** 1-903-270-1187

**E-mail:** [sales@larsonelectronics.com](mailto:sales@larsonelectronics.com)

**The Larson Electronics LEDT8-18W-V1-C-RED-X2 28 watt T-series LED tube lamp is an excellent choice for upgrading existing T8 fluorescent lamp fixtures to LEDs as well as a direct replacement for our own LED light fixtures. This red LED lamp is LEL listed, providing 125 lumens per watt for a total of 2,250 lumens per lamp. These T8 LED replacement lamps offer 50,000 hour lamp life, over twice that of T8 or T5HO fluorescent lamps, while offering impact and vibration resistance far exceeding traditional light sources. The LEDT8-18W-V1-C-RED-X2 features dual-sided power ends that has line voltage going to one end and the neutral line going to the other end.**

This 18 Watt T-series LED Bulb with dual sided power ends works with any T8 fluorescent light fixtures, can be configured for any T series fluorescent lamp fixture with G13 bi-pin tombstones or sockets, and requires no ballast for operation. To increase safety during installation and routine maintenance, these

lamps are wired for dual sided power with internal integrated LED driver housed within the tube. Internally, you simply bring the black wire to one end and the white wire to the other. The polycarbonate lens diffuses the light and makes this bulb ideal for food safe environments as there is no glass. The aluminum housing serves as a heat sink and provides rigidity and strength for this LED bulb.

In fluorescent light fixtures with electronic ballasts, the operator needs to bypass the ballast and wire the power directly to one end of the LED tube and the neutral wire to the other end (black wire to one end and white wire to the other). The correct ends for each are clearly marked on each bulb to prevent incorrect wiring. Thus, this is an ideal upgrade for 4 foot fixtures with failed ballasts. These LED fluorescent style bulbs are universal voltage and run directly off any voltage ranging from 100 volts to 277 volts AC 50/60 Hz. The internal LED driver is a "smart" driver, sensing the incoming voltage and adjusting accordingly to provide the current required by the lamp. This allows operators to simply wire the fixture to voltage within the 120-277V range, no modifications required. This includes commonly found voltages such as 120V 60Hz, 220V 50Hz, 240V 60Hz, and 277V 60Hz. We also offer a 12/24V AC/DC version for low voltage applications for AC or DC power (positive to one end, negative to the other). Low voltage fixtures require no modifications between 12V and 24V power sources, nor between alternating and direct current supply.

---

[Click Photo to Enlarge](#)

[Click Photo to Enlarge](#)

---

Unlike gas burning and arc type lamps that have glass bulbs, LEDs have no filaments or fragile housings to break during operation. Instead of heating a small filament or using a combination of gases to produce light, light emitting diodes (LEDs) use semi-conductive materials that illuminate when electric current applied and emitting light. With LED lights, there is no warm up time or cool down time before re-striking and provide instant illumination when powered on, adding to the reliability of LED technology. By nature, LED light sources run significantly cooler than traditional lamps, reducing the chance of accidental burns and increased temperatures due to heat emissions. This solid state design of light emitting diodes provides a more reliable, stable, durable, and energy efficient light source over traditional lighting.

The LEDT8-18W-V1-C-RED-X2 features specially designed rotating end caps. Fluorescent lamps provide a full 360° beam coverage around the lamp. Since most fluorescent fixtures require directional lighting, reflectors have to be used to bounce the light back towards the intended target area for illumination. LED lamps are directional, which eliminates the need for back mounted reflectors and reduces wasted and lost light. However, the tombstones for existing fixtures may position the face of the LED lamp in a direction facing away from the target illumination area. With the rotating pins, operators can reposition the lamp so the face of the LED tube is positioned properly within existing fixtures. This also allows for fine tune adjustment of each individual lamp within fixtures containing multiple lamps.

These are the second generation of our 18 watt LED tubes. Efficiency for this red LED lamp is 125 lumens per watt, for a total of 2,250 lumens per bulb. The LEDT8 series of LED lamps are designed for direct replacement of 4ft fluorescent fixtures with G13 bases for replacing four foot T8, T8 high output, T12, T12 high output, and T12 very high output florescent lamps. Additionally, these lamps can be used in fixtures that currently use a G5 to G13 adapter socket using T5 lamps. Please

note, this tube is 47" in length and will not fit properly in fixtures designed to accept 45" T5 lamps without adapters.

These LED fluorescent tube replacements can be used as upgrades or replacements to our own explosion proof fluorescent lights, explosion proof paint spray booth lights as well as any other T series light fixture the operator already has in house. We have specially designed these for our explosion proof light fixtures, however, they can be used as replacements in standard fluorescent light fixtures. In our facilities, we replaced worn or spent fluorescent bulbs with these LED bulbs by removing the ballasts and bringing the white wire to one end and the black wire to the other end of the LED tube.

---

### **LED Lamp Benefits**

1. 50,000 hour lifespan.
2. Can SAVE 50% or more on energy.
3. Qualifies retrofit projects for financial incentives, including utility rebates, tax credits and energy loan programs.
4. Reduces energy use and prolongs life-spans of peripheral cooling units (A/C, refrigeration)
5. 100% recyclable.
6. No toxins-lead, mercury.
7. No UV light, infrared radiation or CO2 emissions.
8. Qualifies buildings for LEED and other sustainable business certifications.
9. Bright, even light maintains consistent color over time.
10. Instant on/off - No flickering, delays or buzzing.
11. Very good color rendering.
12. Vibration/impact resistant.
13. Significantly cooler operation.
14. Less frequent outages, higher output improves workplace safety.
15. Brings out natural appearance of products in sales or manufacturing applications.
16. Preserves integrity of retail products... no heat damage to formulations or thermal fade of branded packaging in display cases.
17. Unlimited indoor applications for overhead lighting, retail fixtures, signage, custom lighting accents, manufacturing and general area illumination.
18. Easily retrofit existing conventional light fixtures, simplifies troffers since no ballasts are needed. Durable enough for portable use in exhibitions and trade shows.

Larson Electronics LLC  
9419 E US HWY 175, Kemp, TX 75143  
Phone: 800.369.6671



[www.LarsonElectronics.com](http://www.LarsonElectronics.com)  
Email: [sales@LarsonElectronics.com](mailto:sales@LarsonElectronics.com)  
Fax: 903.498.3364

---

Larson Electronics LLC  
9419 E US HWY 175, Kemp, TX 75143  
Phone: 800.369.6671



[www.LarsonElectronics.com](http://www.LarsonElectronics.com)  
Email: [sales@LarsonElectronics.com](mailto:sales@LarsonElectronics.com)  
Fax: 903.498.3364

---



---

## Frequently Asked Questions (FAQ)



**Warranty:** 12 Months

**Options:**

**LEDT8-18W-V1-C-RED-X2-Diffusion-Voltage**

**Example:** LEDT8-18W-V1-C-RED-X2-CLR-1227

Diffusion	
CLEAR	-CLR
FROSTED	-FRST
HEAVY FROST	-HIFRST

Voltage	
110-277 VAC	-1227
11-25V AC/DC	-1224



Links (Click on the below items to view):

- [Canadian CEC Certificate \(Commonly referred to as CSA Certificate\)](#)
- [USA NEC Certificate \(Commonly referred to as UL Certificate\)](#)
- [HigResPic1](#)
- [HigResPic2](#)
- [Video1](#)
- [ISO 9001 Certification](#)
- [Business Certificate](#)
- [Shipping Time Map](#)