

# FAP-440 Dual Ray Detectors

www.boschsecurity.com



**BOSCH**  
Invented for life



- ▶ Dual Ray Technology provides better particle size differentiation resulting in fewer false alarms
- ▶ Smoke threshold is adjustable and automatically compensated
- ▶ Rotary switch addressing
- ▶ Flexible work modes determined by the control panel
- ▶ Selectable base locking mechanism prevents malicious removal of the detector

The FAP-440 Dual Ray Detectors are open-area smoke detectors of which some models are enhanced with heat or heat and CO sensors. These detectors work with the FPA-1000 Analog Addressable Fire Panels. Use the detector with the FAA-440 bases to provide general life safety and property protection.

## Functions

### Address Range

The FAP-440 Dual Ray Detectors have a valid address range from 1 to 254 which is set by rotary switches on the back of the detector.

### Indicator LED

The detector head has a multi-color LED to indicate status. To verify power to the detector and functioning communication of the analog addressable loop, the LED indicator flashes green when operating normally (polling). Through panel parameter setting, it is possible to turn on or off operation of the polling indicator. In the event of an alarm condition, the detector LED will always show a steady red light.

### Modular Construction

The FAP-440 Dual Ray Detectors are part of a two-piece modular design for detector assemblies. An FAP-440 Dual Ray Detector attaches to an FAA-440

Series Analog Base. The base's security locking tab prevents any unauthorized detector removal from the base.

### Advanced technology for false alarm reduction

**Dual ray technology:** The detector contains two emitters operating at different wavelengths. The different wavelengths enable better differentiation of particle sizes to distinguish smoke particles from other particles that may be present. This results in fewer false alarms due to dust, water vapor, or cigarette smoke.

**Multi-sensor detector:** The multi-sensor detector contains a photoelectric smoke sensor and a heat sensor. Either sensor can detect a fire and activate an alarm signal. The smoke threshold is adjustable (see Sensitivity Calibration and Compensation below) while the heat sensor's threshold is set at 135°F.

**Multi-criteria detector:** The multi-criteria detector also contains smoke and heat sensors that work independently of each other, but in conjunction with the CO sensor. In this model, an alarm signal will be activated by either one or both of the sensors only if the CO level is also exceeded.

**Notice****Carbon monoxide sensors:**

Detectors that contain carbon monoxide (CO) sensors must not be used as stand-alone CO detectors. The CO sensor is supplied to confirm the presence of CO as a by-product of combustion thereby reducing false alarms, but not to confirm the presence of CO as a hazardous gas.

**Programming**

Local programming is carried out at the panel keypad or by computer through a Web browser. Remote programming is carried out through a Web browser.

**Sensitivity Calibration and Compensation**

The sensitivity of the smoke sensor is programmable with 12 levels from which to choose. Throughout its normal life cycle, the smoke detector monitors itself against its factory calibrated level and periodically compensates itself to keep the sensitivity at its programmed level. When the detector is excessively contaminated, this condition will be annunciated at the control panel.

**Certifications and approvals**

Region	Certification	
USA	UL	UROX Smoke-automatic Fire Detectors (ANSI/UL 268)
	CSFM	see our website

**Installation/configuration notes****Compatible Products**

The following products are compatible with the FAP-440 Dual Ray Detectors:

Category	Product ID	Product Description
Fire Panels	FPA-1000 Series	Analog Addressable Fire Panels
Fire Panel Accessories	FPE-1000-SLC	Signaling Line Circuit Plug-in Module
Detector Bases	FAA-440-B4	4-inch Analog Standard Base
	FAA-440-B6	6-inch Analog Standard Base
	FAA-440-B4-ISO	4-inch Analog Isolator Base
	FAA-440-B6-ISO	6-inch Analog Isolator Base

**Mounting Considerations**

Detectors are typically mounted on the ceiling. However, if detectors are mounted on a wall, they must be at least 4 in. (10.2 cm), but no more than 12 in. (30.5 cm), below the ceiling. When other devices containing magnets or producing magnetic fields (for example, loudspeakers) are present in the

area, the base must be at least 1 ft (30 cm) from these devices to prevent unwanted activation of the test switch.

*For UL Listing requirements, the spacing between smoke detectors should be no more than 30 ft (9.14 m).*

**Wiring Considerations**

The control panel communicates to the detectors via the analog addressable loop, which allows the use of standard non-twisted, non-shielded wiring for the SLCs.

The following wire gauges were tested and approved:

Wire Gauge	Maximum length
18 AWG (ISO 0.75 mm <sup>2</sup> )	4000 ft (1200 m)
16 AWG (ISO 1.5 mm <sup>2</sup> )	6225 ft (1900 m)
14 AWG (ISO 2.5 mm <sup>2</sup> )	7200 ft (2200 m)
12 AWG (ISO 4 mm <sup>2</sup> )	9850 ft (3000 m)

**Remote Indicator**

If a remote indicator is used in the circuit, it must be no more than 10 ft (3 m) from the base.

**Parts included**

Quant.	Component
1	FAP-440-D/-DT/-DTC Dual Ray Detector
1	Dust cover

**Technical specifications****Electrical****Maximum current consumption at 77°F (25°C) and 39 V bus voltage**

• Standby	0.17 mA
• Alarm	5 mA
• When polled	22 mA ± 20%
Operating voltage (SLC loop):	24 V DC to 41 V DC
Maximum allowable line resistance:	50 Ω

**Environmental**

Protection category:	IP 42
Relative Humidity:	< 95% (non-condensing)
• Installation temperature:	+32°F to +100°F (0°C to +38°C)

**Storage temperatures**

• With CO sensor:	+14°F to +122°F (-10°C to +50°C)
• Without CO sensor:	-13°F to +176°F (-25°C to +80°C)

**Mechanical**

Dimensions	
• Detector:	4.4 in. x 2.0 in. (11.2 cm x 5.1 cm)
• Detector in 4-inch base:	5.0 in. x 2.5 in. (12.7 cm x 6.4 cm)
• Detector in 6-inch base:	7.0 in. x 2.5 in. (17.8 cm x 6.4 cm)
Housing Material:	CYCOLOY/ABS

**Sensor**

Airflow:	4000 ft/min (20 m/s) maximum
----------	------------------------------

**Sensitivities**

• Smoke sensor:	1.25%/ft to 3.5%/ft (4.1%/m to 11.48%/m)
• Heat sensor:	+135°F (+57°C) + RoR

**Trademarks**

All hardware and software product names used in this document are likely to be registered trademarks and must be treated accordingly.

**Ordering information****FAP-440-D Analog Dual-Photoelectric Detector**

Order number **FAP-440-D**

**FAP-440-DT Analog Multisensor Detector Dual-Photo/Heat**

Order number **FAP-440-DT**

**FAP-440-DTC Analog Multicriteria Detector Dual-Photo/Heat/CO**

Order number **FAP-440-DTC**

**Represented by:****Americas:**

Bosch Security Systems, Inc.  
130 Perinton Parkway  
Fairport, New York, 14450, USA  
Phone: +1 800 289 0096  
Fax: +1 585 223 9180  
security.sales@us.bosch.com  
www.boschsecurity.us

**Europe, Middle East, Africa:**

Bosch Security Systems B.V.  
P.O. Box 80002  
5617 BA Eindhoven, The Netherlands  
Phone: + 31 40 2577 284  
Fax: +31 40 2577 330  
emea.securitysystems@bosch.com  
www.boschsecurity.com

**Asia-Pacific:**

Robert Bosch (SEA) Pte Ltd, Security Systems  
11 Bishan Street 21  
Singapore 573943  
Phone: +65 6571 2808  
Fax: +65 6571 2699  
apr.securitysystems@bosch.com  
www.boschsecurity.asia

**China:**

Bosch (Shanghai) Security Systems Ltd.  
201 Building, No. 333 Fuquan Road  
North IBP  
Changning District, Shanghai  
200335 China  
Phone +86 21 22181111  
Fax: +86 21 22182398  
www.boschsecurity.com.cn

**America Latina:**

Robert Bosch Ltda Security Systems Division  
Via Anhanguera, Km 98  
CEP 13065-900  
Campinas, Sao Paulo, Brazil  
Phone: +55 19 2103 2860  
Fax: +55 19 2103 2862  
latam.boschsecurity@bosch.com  
www.boschsecurity.com