

**Part #: 2100-984LR****Size:** 9-7/8" H x 6-5/8" W x 3-1/4" D**Style:** Red Fiberglass, Surface Mount, NEMA 4, Exterior Rated**Options:** Strobe Interface & Relay, Mushroom Push Button**Features:**

- Meets all IBC, ADAAG, and NFPA code requirements
- Requires an analog telephone line (POTS, PBX, or central office line)
- Power Requirements: 24vdc from model 2500-PWR24U
- 7.2V 300mAH battery (part #: RP7300110)
- Built-in battery backup recharges from 24vdc power (allows for a minimum of 4 hours of talk time upon power loss)
- Built-in 10 phone consolidator feature allows you to install 10 Call Boxes and 1 Base Station on a single telephone line
- Programmable with up to 5 emergency numbers
- On-site programming
- Remote or on-site diagnostic test
- Recordable location message (18 seconds)
- Phone checks every 24 hours for an active phone line, if one is not detected, phone will provide a relay trip
- Compatible with the SmartRescue Base Station or Command Center for in-building rescue coordination
- Automatic dialer (31 digit programmable memory)
- Automatic answer feature with audible ring
- Touch Tone operation only (Touch Tone is an AT&T registered trademark)
- Optional strobe interface and relay
- 3 year warranty
- Conforms to UL Standard 2017 for Attendant Monitored Signaling Device
- Complies with Section 6.4 of UL 60950-1
- ETL Listing Number: 5013373



Side View



Back View



Top View

