

## 15 Watt or 30 Watt Public Address Amplifiers

**PVL15A** 15W P.A. mixer amplifier

**PVL30A** 30W P.A. mixer amplifier

### Features

- Mic1 priority mute function with front button
- Separate bass and treble controls



PVL15A



PVL30A



rear of unit



rear of unit

### Specifications

	<b>PVL15A</b>
RMS Output Power.....	15W
Max. Output Power.....	30W
AC Power Consumption.....	60W
Power Supply .....	AC 120V, 50/60Hz
Zones.....	1
Speaker Outputs.....	4/8/16 Ohms, 70/25V
Inputs.....	2 x Mic (1/4" and 1/4" or XLR) 1 x Aux (1/4")
Frequency Response .....	50Hz ~ 15KHz
Tone Control .....	Bass ± 10dB, Treble ± 10dB
THD .....	Less than 0.1% @1KHz
Signal/Noise Ratio .....	Microphone: >75dB, Line: >80dB
Controls .....	Volume for each source, Tone, Priority
Telephone .....	No
Indicators .....	Power
Dimensions.....	8.25" (W) x 3" (H) x 7.9" (D)
Weight .....	8.4 lbs.
Listings .....	CE, FCC, RoHS

	<b>PVL30A</b>
RMS Output Power.....	30W
Max. Output Power.....	60W
AC Power Consumption.....	100W
Power Supply .....	AC 120V, 50/60Hz
Zones.....	1
Speaker Outputs.....	4/8/16 Ohms, 70/25V
Inputs.....	2 x Mic (1/4" and 1/4" or XLR) 1 x Aux (1/4" or RCA)
Frequency Response .....	50Hz ~ 15KHz
Tone Control .....	Bass ± 10dB, Treble ± 10dB
THD .....	Less than 0.1% @ 1KHz
Signal/Noise Ratio .....	Microphone: >75dB, Line: >80dB
Controls .....	Volume for each source, Tone, Priority
Telephone .....	No
Indicators .....	Power
Dimensions.....	8.25" (W) x 3" (H) x 7.9" (D)
Weight .....	10.6 lbs.
Listings .....	CE, FCC, RoHS