Miniature 1-Channel RF Receivers & Transmitters

SK-910RA One-Channel Receiver – 1 Amp Relay Output SK-910RAV One-Channel Receiver – Transistor Group O/P

- Four programmable output modes: -- 4-Second Momentary Output -- Validity Output -- Togale Output -- 1-Second Momentary Output
- Flexible operating voltage: SK-910RA: 11~24 VAC/VDC SK-910RAV: 3~13.8 VDC
- Up to 500ft (152m) range*.
- Controls garage doors, gates, house lights, alarm panels, or other devices via remote.
- Compatible with all 315MHz SECO-LARM transmitters (fixed code and CODEBUMP).
- LED indicates RF reception, learn mode entered, transmitter learned, memory cleared, and relay output mode.

SK-919TD1S-UP Factory Pre-coded Transmitter **SK-919TT1S-BU** DIP-Switch-coded Transmitter

- Operates up to 500ft (152m), 315MHz*.
- LED transmission indicator.
- Includes 12VDC alkaline battery.
- Compatible with all 315MHz SECO-LARM receivers.
- SK-919TD1S-UP: Over 68 billion possible codes.
- SK-919TT1S-BU: Use for "block coding" a large number of transmitters with the same code, or for simple matching of a transmitter already in use.

SK-919TP1H-BU One-Button Handheld Transmitter

- Operates up to 500ft (152m), 315MHz*.
- Over 68 billion (6.8x10¹⁰) possible codes.
- Includes two 3VDC lithium batteries.
- Visor clip and belt clip included. Belt-clip holster & wall-mount bracket also available (Model: SK-9HBC).
- Slimline design.

*Actual range may vary greatly depending on the installation and operating environment

SECO-LARM

16842 Millikan Avenue Irvine, CA 92606

Tel: 1-949-261-2999 1-800-662-0800 Fax: 1-949-261-7326





11/2"x 21/4"x5/8" (38x63x16 mm)

ENFORCER Wireless



213/16"x 31/2"x1/2" (71x89x13 mm)

SK-910RA and SK-910RAV

Specifications:

	SK-910RAQ	SK-910RAV
Range	Up to 500' (150m) in open air	
Operating voltage	11~24 VAC/VDC	3~13.8 VDC
Current draw	5mA Standby, 50mA LED flashing @12 VDC	5mA Standby, 15mA LED flashing @12 VDC
Output mode	Programmable 4s momentary (default), 1s momentary, toggle (ON/OFF), validity	
# of outputs	1	1
Output Type	1A Relay (NO/NC/COM)	5A Transistor GND
Transmitter	Compatible with all SECO-LARM transmitters	

Web: www.seco-larm.com Email: info@seco-larm.com



The SECO-LARM policy is one of continual development. For that reason, SECO-LARM reserves the right to change prices and specifications without notice. SECO-LARM is not responsible for misprints.