

60 Watt P.A. Amplifier with AM/FM Tuner & MP3 Ready CD Player

P60FACD 60W P.A. amplifier

Features

- 4 zoned 70 or 25V speaker outputs
- AM/FM Tuner with 8-function CD player
- Telephone paging input and Music-on-hold output
- Individual volume control for each Mic input
- Front bass and treble controls
- Mic1 selectable priority paging
- UL & CSA listed
- 5 year warranty



rear of unit

Specifications

RMS Output Power..... 60W
 Max. Output Power..... 90W
 AC Power Consumption ... 170W
 Power Supply AC 115V, 50Hz/60Hz
 Zones..... 4
 Speaker Outputs..... 4/8/16 Ohms (non-zoned), 70/25V (zoned)
 Other Outputs Aux (RCA)
 Inputs..... 1 x AM Antenna (Press terminal), 1 x FM Antenna (BNC), 1 x Aux (Stereo RCA), 4 x Mic (XLR), 1 x TEL (terminal)
 Frequency Response 60Hz ~ 15kHz (±3dB)
 Tone Control Bass ± 10dB, Treble ± 10dB
 THD Less than 1% @ 1kHz
 Signal/Noise Ratio 70dB
 Controls Volume for each Mic, Master Volume, Vox Volume, MoH Volume, Vox Selector, Tone, Source Selector, Zone Selector, Tuner and CD
 Telephone TEL in and MoH Out
 Indicators Tuner, CD, power, power level
 Dimensions..... 16.9" (W) x 3.5" (H) x 11.6" (D)
 Weight 21.4 lbs.
 Listings UL, cUL, CSA, CE, FCC

Rack mounting kit available: **PBMRK2**

NDAA
COMPLIANT

*Products are in compliance with NDAA Section 889 Part B Guidelines