


The Transmitter Solutions® Stingray 295SEPA2V is a visor transmitter operating at 295 MHz. It has been designed for use with Wiegand 26-bit programmable telephone entry systems, anti-burglar systems and access control systems operating with a 295 MHz input. This transmitter is compatible with the Sentex® AUTOkey-2.

Compatible with:
Sentex® AUTOkey-2



FEATURES

- 295 MHz
- Two Button (White)
- Visor Model
- Sentex® AUTOkey-2 Compatible
- 5 Year Warranty
- Programmable




Also available in 1 button.



295SEPA1V

SPECIFICATIONS

Supply : 1 Alkaline Battery 12V type 23A
 Battery life: 12 - 18 months
 Current consumption : 20 mA
 Code combinations : 16,777,216
 Modulation : AM / ASK
 Range in free space: 60 - 120 yd
 Operating temperature: -20 ÷ +55 °C
 Overall dimensions: 3.26 x 1.88 x 0.62 in
 Weight: 1 oz. (20 gr.)



KEEP YOUR CUSTOMERS COMING BACK!

We can brand your transmitter with your logo and information.