PPro[™] **IP-based** Access Control Starter Kit

he IP Pro is a single door IP controller with expandibility, supporting up to 15,000 users.



Designed for ease of use, the IP Pro embedded software allows for real-time monitoring and user management via a web browser.





FEATURES

- Controls one door directly, with unlimited expansion capabilities
- TCP/IP communications (100/10Mbps)
- **DHCP** or Static IP addresses
- Password protected built-in web server (No separate software to install)
- Live transaction monitoring
- Entry & exit reader capability
- Supports industry standard proximity, smart card, and multi-technology readers (Wiegand output)
- Reader short circuit protection
- Compliant with PoE+ standard

- 15,000 users (up to 2 credentials per user)
- Batch card enrollment
- 250 User groups/Time Zones/Door Groups
- Holiday support
- Scheduled Events
- **Temporary Users**
- Audit Trail Up to 5,000 events may be exported as a .csv file
- Status LED's Power, Communications, & Fault on-board diagnostic indicators
- Anti-tailgating
- Anti-passback (global or localized)

- Supported browsers: Microsoft Internet Explorer 8 & 9, Firefox 8.0, Google Chrome
- Multiple credential modes: Card only, PIN only, Pin or Card, Pin & Card
- Door Status Monitoring Input
- Request-to-Exit (REX) Input
- Programmable Auxiliary Input
- Lock Relay Output
- Auxiliary Relay Output
- (2) Programmable Solid-state Outputs
- Tamper Input
- Database backup support

MODELS

IPPRO-SKE IP Pro Starter Kit, including Controller board, Splitter and

Injector components plus Controller enclosure

IP Pro Starter Kit, including Controller board, Splitter, Injector **IPPRO-SK**

IPI-30 IP Pro Injector 30W PoE+ **IPS-12** IP Pro Splitter 12VDC PoE+ **IPDC** IP Pro Controller board only

IPDCE IP Pro Controller board plus enclosure

IPDSE IP Pro Door Station Expansion board plus enclosure


IPDS IP Pro Door Station Expansion board only

IPRW IP Pro Wiegand Reader - PROX, HID compatible (125 kHz)





Pro Solution





IP Pro Controller

/ Door Station Expansion


/ Door Station Expansion	
Voltage	12 VDC Input
Current Consumption (max)	250mA - Controller 120mA - Door Station Expansion
Operating Temperature	14°F – 122°F (Indoor use only)
Dimensions	5.375" x 3.5" x 0.875" board only 9.25" x 6.5" x 2.1875" w/ ABS plastic enclosure
Weight	1lb
Relay Output Type	Form C (SPDT) x 2
Relay Contact Rating	Main (Lock) – 5A @ 30VDC Auxiliary – 1A @30VDC
Connections	Digital Inputs: 4 dry contact inputs Ethernet: RJ45 (Controller only) RS-485 Terminal Bus Reader Power – 12VDC Reader Data – Wiegand (26bit to 37bit)

IP Pro Splitter

Input voltage	44 - 57 VDC	
Input power	30W max	
Output power	24W max	
Output Current	2A @ 12V	


IP Pro Injector


PoE+ Output Pin Assignment and Polarity	4/5 (+), 7/8 (-)
Output Power Voltage	55Vdc
User Port Power	30Watts (Guaranteed)





Reader LED Control – Red & Green Two Solid State outputs (100mA max)





Please see our PoE brochure for a complete lineup of low-current Access Control Hardware, which are guaranteed to work with the IP Pro™ Series

